

## VSIP3MPVDIR SD card recording

1. To set up a VSIP2MPVDIR camera to enable SD card recording first insert an SD card into the camera.
2. Plug the camera in to your local network and Power on the camera.
3. Connect to the cameras web interface by typing its IP address in Internet Explorer. For example <http://192.168.0.108/>
4. Default Username: admin  
Default Password: admin
5. Enter the cameras *Setup* menu, followed by the *Storage, Destination*. Choose to Record on Timer or Motion for *Local*. Then Choose *the Local* Tab at the top. Here you should be able to see the SD card listed. Select the SD card from the list and click to *Format* the SD card for use in the camera.
6. Next go in to *Schedule*. You will need to make sure the *Schedule* is set for *General* or *Motion Recording* on all Days and save.
7. Once this completed, choose *Reboot Device (System then Auto Maintain)*.
8. Once the camera has rebooted it will be ready to record. You can check this by waiting 10 minutes and logging in to the camera. You can now enter *Playback, Search* a time and be able to play back video footage. (In *HDD Management*, you will also see the free space decreasing).